

Modifying the Netopia R3100 for LAN-ISDN Service

Changing the Dial Up Phone Number

Our internet access phone numbers can be retrieved via e-mail at numbers-info@psi.com or via our FaxBack server by dialing 518-283-8860 and choosing option 4. Follow the prompts, select code number 1002, and key in your fax number. **Please be sure to check with your telephone company to insure it is a local call, as long distance charges will apply and be your sole responsibility.**

Use the arrow keys to move the cursor within the menus. With the field highlighted you may change it, then hit enter to accept. Esc will cancel or if you're in a sub menu it will return you to the previous menu.

From the Main Menu choose:

Easy Setup...

then select **NEXT SCREEN** to reach the following screen:

```
Connection Profile 1: Easy Setup Profile

Number to Dial:                19103332366

Address Translation Enabled:    No
IP Addressing...               Unnumbered

Remote IP Address:             38.1.1.1
Remote IP Subnet:              255.0.0.0

PPP Authentication...          PAP
Send User Name:                LI0CSG
Send Password:                 *****

PREVIOUS SCREEN                NEXT SCREEN
```

Using the arrow keys, move to the phone number field, make your change and hit **enter**.

Select **NEXT SCREEN** on each menu until you see **RESET DEVICE**. Select it and hit enter. This will save your change(s) and restart the router.

